

## PM2018S

### SMART 600A AC CLAMP METER



- New generation **intelligent** (auto function & auto range) meter, just turn on and measure!
- 6,000 counts LCD dual display with backlit
- Non-contact AC voltage detection (**NCV**)
- **LPF** (low-pass filter) of 1kHz, 3dB.
- Frequency measurement by clamp or leads
- Data hold, Peak Max value measurement
- Auto power off
- Safety as per IEC1010-1 CAT.III 600V

#### Technical specifications

DCV: 6/60/600V, min 0.5V;  $\pm 0.5\%$   
ACV(40~65Hz): 6/60/600V, min 1.0V;  $\pm 0.8\%$   
ACA(40~65Hz): 6/60/600A, min 10mA;  $\pm 2.5\%$   
PEAK ACA: 10A~900A,  $\pm 10\%$   
OHM: 6k/60k/600k/6M/10M  $\Omega$ ,  $\pm 0.8\%$   
FREQ: 40Hz~1kHz,  $\pm 1.0\%$   
Audible continuity: <30  $\Omega$   
Clamp size:  $\Phi 24\text{mm}$  (max.)  
Battery: 1.5Vx2, AAA size  
Dimensions: 187x65x38mm, 250g approx.  
Accessories: carrying bag

**PEAKMETER**<sup>®</sup>

by Sinometer

[www.peak-meter.cn](http://www.peak-meter.cn)

Email: [sales@peak-meter.cn](mailto:sales@peak-meter.cn)